

DIGITAL VIDEO RECORDER



INSTALLATION NOTES:
 *RUN A 18 AVG UTP CABLE FROM THE DATA DEVICE (CASH REGISTER) LOCATION TO THE IMAGE VAULT LOCATION. (IF THE CABLE LENGTH IS GOING TO EXCEED 75' WE RECOMMEND CAT 5 CABLE).
 *UNPLUG THE DB25 FROM THE BACK OF THE PRINTER AND INSTALL THE DB25P CONNECTOR, (PART # IV-25) AT THE END OF THE EXISTING CABLE AND CONNECT THE OTHER END BACK TO THE PRINTER.
 *SPlice THE DIGITAL LEADS FROM THE DB25P TO THE CABLE THAT WAS RAN FROM THE DATA DEVICE, (CASH REGISTER) TO THE DVR. (SEE WIRING CONSIDERATIONS BELOW)
 *SPlice THE DB9F CONNECTOR DIGITAL LEADS TO THE DVR END OF THE CABLE THAT WAS RAN.
 PLEASE REFER TO THE USERS MANUAL

*ONCE ALL OF THE CONNECTIONS ARE MADE, THE DVR STILL NEEDS TO BE CONFIGURED - GOTD THE "STATUS" MENU, AND SELECT "EDIT DATA STREAM SETUP"

*ENABLE THE PORT BY CHECKING THE BOX "IS PORT IN USE?" *THEN ENABLE THE DEVICE, BY CHECKING THE BOX "IS DEVICE IN USE?" YOU CAN NAME THE DEVICE BY DOUBLE CLICKING IN THE WHITE AREA OF THE "DEVICE NAME" FIELD NEXT, SELECT THE DEVICE TYPE BY CLICKING IN THE WHITE AREA OF THE "DEVICE TYPE" FIELD.
 *FINALLY, ASSIGN A PARTICULAR CAMERA TO THE PORT.

*IF YOU HAVE 2 DATA DEVICES - PORT #2 NEEDS TO BE CONFIGURED ALSO. IN THE UPPER LEFT HAND CORNER THERE IS A DROP DOWN LIST THAT ALLOWS YOU TO SELECT EITHER PORT #1 OR PORT #2.

*AFTER ALL OF THE ABOVE IS COMPLETED - REBOOT THE DVR.



WIRING CONSIDERATIONS:
 *ONLY 2 OF THE WIRES ON THE DB25P WILL BE USED AT ANY TIME.
 *THE BLACK LEAD ON THE DB25P WILL ALWAYS BE USED AND CONNECTED TO THE BLACK LEAD OF THE DB9F.
 *ON A TYPICAL INSTALLATION WHEN THE DB25P IS LOCATED AT THE PRINTER, THE WHITE LEAD OF THE DB25P WILL
 SPlice TO THE RED LEAD ON THE DB9F.
 *ON INSTALLATIONS WHERE IT IS NECESSARY FOR THE DB25P TO BE LOCATED AT THE PC, THE RED LEAD OF THE DB25P WILL SPlice TO THE RED LEAD OF THE DB9F.

11/2001		© COPYRIGHT 2001	
IV-25		IMAGE VAULT TECHNICAL SERVICES	
DESCRIPTION:		101 SECURITY PKWY. NEW ALBANY, IN 47150 (888) 462-4382	
IV-25 DB25 SERIAL INTERFACE IVTECH@FIREKING.COM			
REVISION:	1.	SCALE:	NTS
2.			
3.			
4.			
ARCHITECT:	JCA		
DRAWN BY:	JCA		
CHECKED BY:	JCA		
DATE:	11/14/2001		